

5/29/2014



**PRODUCT RELIABILITY REPORT
FOR**

MAX31730

Maxim Integrated

**14460 Maxim Dr.
Dallas, TX 75244**

Approved by:

**Sokhom Chum
SMTS, Reliability Engineering**

Conclusion:

The following qualification successfully meets the quality and reliability standards required of all Maxim Integrated products:

MAX31730

In addition, Maxim Integrated's continuous reliability monitor program ensures that all outgoing product will continue to meet Maxim's quality and reliability standards. The current status of the reliability monitor program can be viewed at <http://www.maximintegrated.com/qa/reliability/monitor>.

Device Description:

A description of this device can be found in the product data sheet. You can find the product data sheet at <http://www.maximintegrated.com/search/parts.mvp>.

Reliability Derating:

The Arrhenius model will be used to determine the acceleration factor for failure mechanisms that are temperature accelerated.

$$AfT = \exp((Ea/k) * (1/Tu - 1/Ts)) = tu/ts$$

AfT = Acceleration factor due to Temperature
tu = Time at use temperature (e.g. 55°C)
ts = Time at stress temperature (e.g. 125°C)
k = Boltzmann's Constant (8.617 x 10⁻⁵ eV/°K)
Tu = Temperature at Use (°K)
Ts = Temperature at Stress (°K)
Ea = Activation Energy (e.g. 0.7 eV)

The activation energy of the failure mechanism is derived from either internal studies or industry accepted standards, or activation energy of 0.7eV will be used whenever actual failure mechanisms or their activation energies are unknown. All deratings will be done from the stress ambient temperature to the use ambient temperature.

An exponential model will be used to determine the acceleration factor for failure mechanisms, which are voltage accelerated.

$$AfV = \exp(B * (Vs - Vu))$$

AfV = Acceleration factor due to Voltage
Vs = Stress Voltage (e.g. 7.0 volts)
Vu = Maximum Operating Voltage (e.g. 5.5 volts)
B = Constant related to failure mechanism type (e.g. 1.0, 2.4, 2.7, etc.)

The Constant, B, related to the failure mechanism is derived from either internal studies or industry accepted standards, or a B of 1.0 will be used whenever actual failure mechanisms or their B are unknown. All deratings will be done from the stress voltage to the maximum operating voltage. Failure rate data from the operating life test is reported using a Chi-Squared statistical model at the 60% or 90% confidence level (Cf).

The failure rate, Fr, is related to the acceleration during life test by:

$$Fr = X / (ts * AfV * AfT * N * 2)$$

X = Chi-Sq statistical upper limit
N = Life test sample size

Failure Rates are reported in FITs (Failures in Time) or MTTF (Mean Time To Failure). The FIT rate is related to MTTF by:

$$\text{MTTF} = 1/\text{Fr}$$

NOTE: MTTF is frequently used interchangeably with MTBF.

The calculated failure rate for this device/process is:

FAILURE RATE: **MTTF (YRS):** **4061** **FITS:** **28.1**
DEVICE HOURS: **32595855** **FAILS:** **0**

Only data from Operating Life or similar stresses are used for this calculation.

The parameters used to calculate this failure rate are as follows:

Cf: 60% **Ea: 0.7** **B: 0** **Tu: 25 °C** **Vu: 3.6 Volts**

The reliability data follows. At the start of this data is the device information. The next section is the detailed reliability data for each stress. The reliability data section includes the latest data available and may contain some generic data. **Bold** Product Number denotes specific product data.

Device Information:

Process: TSMC 0.18um Mixed signal, General Purpose, Single poly Quad metal, 1.8V/3.3V
 Passivation: SiO/SiN
 Die Size: 62 x 87
 Number of Transistors: 65963
 Interconnect: Aluminum / 0.5% Copper
 Gate Oxide Thickness: 32 Å

ESD HBM

DESCRIPTION	DATE	CODE/PRODUCT/LOT	CONDITION	READPOIN	QTY	FAILS	FA#
ESD SENSITIVITY	1350	MAX31730	ZJ141626DB JESD22-A114 HBM 500 VOLTS	1	PUL'S	5	0
ESD SENSITIVITY	1350	MAX31730	ZJ141626DB JESD22-A114 HBM 1000 VOLTS	1	PUL'S	5	0
ESD SENSITIVITY	1350	MAX31730	ZJ141626DB JESD22-A114 HBM 1500 VOLTS	1	PUL'S	5	0
ESD SENSITIVITY	1350	MAX31730	ZJ141626DB JESD22-A114 HBM 2000 VOLTS	1	PUL'S	5	0
ESD SENSITIVITY	1350	MAX31730	ZJ141626DB JESD22-A114 HBM 2500 VOLTS	1	PUL'S	5	0
Total:						0	

LATCH-UP

DESCRIPTION	DATE	CODE/PRODUCT/LOT	CONDITION	READPOIN	QTY	FAILS	FA#
LATCH-UP I	1350	MAX31730	ZJ141626DB JESD78A, I-TEST 25C 100mA			6	0
LATCH-UP I	1350	MAX31730	ZJ141626DB JESD78A, I-TEST 25C 250mA			6	0
LATCH-UP V	1350	MAX31730	ZJ141626DB JESD78A, V-SUPPLY TEST 25C			6	0
Total:						0	

OPERATING LIFE

DESCRIPTION	DATE	CODE/PRODUCT/LOT	CONDITION	READPOIN	QTY	FAILS	FA#
HIGH TEMP OP LIFE	1243	DS28E05	ZH132976DB 125C, 3.6 VOLTS	192 HRS	80	0	
HIGH TEMP OP LIFE	1309	MAX2082	KAHZ1AQ0 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	500 HRS	25	0	
HIGH TEMP OP LIFE	1309	MAX2082	KAHZ1AQ0 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	192 HRS	22	0	
HIGH TEMP OP LIFE	1309	MAX2082	KAHZ1AQ0 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	500 HRS	25	0	
HIGH TEMP OP LIFE	1327	MAX2082	KAHZ1AGQ2 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	500 HRS	25		
HIGH TEMP OP LIFE	1327	MAX2082	KAHZ1AGQ2 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	500 HRS	23	0	
HIGH TEMP OP LIFE	1328	MAX2082	KAHZ1AGQ3 120C Ambient; SEE PROJECT SPECIAL INSTRUCTIONS !	500 HRS	22	0	
HIGH TEMP OP LIFE	1350	MAX31730	ZJ141626DB 125C, 3.6 VOLTS	240 HRS	80	0	

Total: 0

FAILURE RATE: **MTTF (YRS):** **4061** **FITS:** **28.1**
DEVICE HOURS: **32595855** **FAILS:** **0**